

# THE TRIBAY SERIES COMPLETE FIXTURE MATRIX BALLAST HOUSING AND OPTICAL ASSEMBLY, AVAILABLE COMBINATIONS SUPERBAY 2.0 SERIES

These fittings are supplied for field assembly into a complete high intensity discharge fixture and are grouped into ballast housings and optical assemblies. The chart below indicates the ballast housing and optical assembly combinations that go together to make listed fixtures. All options that appear as -.... suffixes to the ballast housing or optical assembly catalog numbers are included. Unless the CH-xx-x-x-E or -L- is chosen, the ballast housing is supplied with a mounting hanger included in the carton. When this option is chosen one of the following mounting hangers is required for field assembly to the ballast housing: CH-B or CH-Q. In addition, a suitable optical assembly from the table below must also be field assembled to this ballast housing to form a complete fixture. Optional lens assemblies may be added to specific reflectors in the field to provide a bottom enclosure. The table indicates the appropriate lens assembly that fits onto the specific reflector. The table relates the ballast housing catalog numbers in the left column and the optical assembly catalog numbers across the top and the associated lens assemblies. The body of the table is filled in with letters whose designation is listed as follows:

- Y - acceptable combination
- C - conditionally acceptable combination-must use applicable lens attachment or marking
- not acceptable combination

OPTICAL ASSEMBLY CAT. NO. (2)	CH-EU-...	CH-EU-60-...	CH-OU-...	CH-OU-60-...	(3) NOTES AND MARKINGS
BALLAST HOUSING CAT. NO. (1)					
CHA10-*8-M-E		Y			
CHA10-*8-M-O				Y	
CH-10-*x-x-EU-... or -NA-....		Y			
CH-10-*x-x-OU-... or -NB-....				Y	
* = H or S					
CH-60-S-x-x-EU-... or -NA-....		Y			
CH-60-S-x-x-OU-... or -NB-....				Y	
CHA40+-8-M-E	Y				
CHA40+-8-M-O			Y		
CH-40+-x-x-EU-... or -NA-....	Y				
CH-40+-x-x-OU-... or -NB-....			Y		
+ = H, S, E, D, M, L, or F					
CH-35-S-x-x-EU-... or -NA-....	Y				
CH-35-S-x-x-OU-... or -NB-....			Y		
CH-25-&-x-x-EU-... or -NA-....	Y				
CH-25-&-x-x-OU-... or -NB-....			Y		
& = S, M, L or F					
CH-25-o-x-x-EU-... or -NA-....	Y				
CH-25-o-x-x-OU-... or -NB-....			C4		4 = REQUIRES CH-ENC-19
o = H, E, or D					
APPLICABLE LENS ATTACHMENT (4) CAT. NO.			CH-ENC-19	CH-ENC-23	



Hubbell Lighting, Inc.  
 A Subsidiary of Hubbell Incorporated  
 2000 Electric Way  
 Christiansburg, VA 24073-2500  
 (703) 382-6111  
 FAX (703) 382-1526

Original Drawing

268-0969-9901